

Technical Data	GW3600-EH	GW5000-EH	GW6000-EH
Battery Input Data*			
Battery Type	Li-Ion	Li-Ion	Li-Ion
Battery Voltage Range(V)	85~450	85~450	85~450
Start-up Voltage (V)	90	90	90
Max. Charging/Discharging Current (A)	25/25	25/25	25/25
Max. Charging/Discharging Power (W)	3600	5000	6000
Battery Ready Optional Function	YES	YES	YES
PV String Input Data			
Max. DC Input Power (W)	4800	6650	8000
Max. DC Input Voltage (V)	580	580	580
MPPT Range (V)	100~550	100~550	100~550
Start-up Voltage (V)	90	90	90
Nominal DC Input Voltage (V)	380	380	380
Max. Input Current (A)	12.5/12.5	12.5/12.5	12.5/12.5
Max. Short Current (A)	15.2/15.2	15.2/15.2	15.2/15.2
No. of MPP Trackers	2	2	2
No. of Strings per MPP Tracker	1	1	1
AC Output Data (On-grid)			
Nominal Apparent Power Output to Utility Grid (VA)*2	3600	5000	6000
Max. Apparent Power Output to Utility Grid(VA)*2	3600/3960*1	5000/5500*1	6000/6600*1
Max. Apparent Power from Utility Grid (VA)	7200 (Charging 3.6kw,backup output3.6kw)	10000 (Charging 5kw,backup output 5kw)	12000 (Charging 6kw,backup output 6kw)
Nominal Output Voltage (V)	230	230	230
Nominal Output Frequency (Hz)	50/60	50/60	50/60
Max. AC Current Output to Utility Grid (A)*2	16/18*1	21.7/24*1	26.1/28.7*1
Max. AC Current From Utility Grid (A)	32	43.4	52.2
Output Power Factor	~1 (Adjustable from 0.8 leading to 0.8 lagging)		
Output THDi (@Nominal Output)	<3%	<3%	<3%
AC Output Data (Back-up)*			
Max. Output Apparent Power (VA)	3600	5000	6000
Peak Output Apparent Power (VA)	4320 ,60sec	6000 ,60sec	7200 ,60sec
Max. Output Current (A)	15.7	21.7	26.1
Automatic Switch Time (ms)	<10		
Nominal Output Voltage (V)	230 (±2%)	230 (±2%)	230 (±2%)
Nominal Output Frequency (Hz)	50/60 (±0.2%)	50/60 (±0.2%)	50/60 (±0.2%)
Output THDv (@Linear Load)	<3%	<3%	<3%
Efficiency			
PV Max. Efficiency	97.6%	97.6%	97.6%
PV European Efficiency	97.0%	97.0%	97.0%
PV Max. MPPT Efficiency	99.9%	99.9%	99.9%
Battery Charged By PV Max. Efficiency	98%	98%	98%
Battery Charge/discharge From/To AC Max. Efficiency	96.6%	96.6%	96.6%
Protection			
Anti-Islanding Protection	Integrated	Integrated	Integrated
Battery Input Reverse Polarity Protection	Integrated	Integrated	Integrated
Insulation Resistor Detection	Integrated	Integrated	Integrated
Residual Current Monitoring Unit	Integrated	Integrated	Integrated
Output Over Current Protection	Integrated	Integrated	Integrated
Grid Output Short Protection	Integrated	Integrated	Integrated
Output Over Voltage Protection	Integrated	Integrated	Integrated
General Data			
Operating Temperature Range (°C)	-35~60	-35~60	-35~60
Relative Humidity	0~95%	0~95%	0~95%
Operating Altitude (m)	4000	4000	4000
Cooling	Natural Convection		
Noise (dB)	<35	<35	<35
User Interface	LED & APP	LED & APP	LED & APP
Communication with BMS	CAN	CAN	CAN
Communication with Meter	RS485	RS485	RS485
Communication with Portal	Wi-Fi/Ethernet(Optional)		
Weight (kg)	17	17	17
Size (Width*Height*Depth mm)	354*433*147	354*433*147	354*433*147
Mounting	Wall Bracket	Wall Bracket	Wall Bracket
Protection Degree	IP65	IP65	IP65
Standby Self Consumption (W)*3	<10	<10	<10
Topology	Transformerless		
Certifications & Standards			
Grid Regulation	AS/NZS 4777.2:2015; G98/1; CEI 0-21 VDE4105-AR-N	AS/NZS 4777.2:2015; G99/1; CEI 0-21;VDE4105-AR-N	
Safety Regulation	IEC/EN62109-1&-2		
EMC	EN61000-6-1, EN61000-6-2, EN61000-6-3, EN61000-6-4, EN61000-4-16, EN61000-4-18, EN61000-4-29		

*1 for CEI 0-21.

*2 The grid feed in power for VDE-AR-N 4105 and NRS097-2-1 is limited 4600VA, for AS/NZS 4777.2 is limited 4950VA & 21.7A.

*3 No Back-up Output

*: An activation code is required when connecting to an approved Lithium-Ion Battery. It can be purchased from GoodWe's authorized dealers or distributors.

GoodWe only acknowledges the activation code purchased from our authorized dealers or distributors.

GoodWe's Smart Meter, an optional accessory, is able to monitor load consumption. It can be purchased through authorized dealers or distributors.